

Configuración para registro a la red celular





En el Web browser ingresar la IP **192.168.1.1** luego, se desplegara la siguiente página en la cual, se deben ingresar los siguientes datos.

Username: username

Password: password



TransPort WR21 (SN: 416884) Configuration and Management

Login		System
Username	Model:	TransPort WR21
	Part Number:	WR21-U91B-DB1-SW
Password	Serial Number:	416884
Log in	Uptime:	1 minutes 2 seconds
	System Time:	20 Aug 2015 16:12:01
	CPU Utilization:	1% (Min: 1%, Max: 54%, Avg: 1%)
	Temperature:	35°C (CPU)
	Description:	Transport WR21
	Contact:	Marketing Relacional y Fidelizacion
	Location:	Wamtech
	Ethernet	Interface Status
	Cellular 🧯	

Una vez realizado lo anterior, se debe desplegar la siguiente panatlla.



Una vez que se desplegó la pantalla anterior, se debe ingresar a **Condiguration**-**Network>Interfaces>Mobile** y de ahí, se debe ingresar a la pestaña Mobile Settings

User : username	Configuration - Network > Interfaces > Mobile	
	* Interfaces	_
Homo	Ethernet	
Wizards	Mobile	
Configuration	Select a SIM to configure from the list below	
Network	Select a STA to compare nom the list below	
Alarms	Settings on this page apply to the selected SIM	
System	SIM: 1 (PPP 1) V	
Remote Management	IMSI: Linknown	
Security		
Position	▼ Mobile Settings	
Applications	Select the service plan and connection settings used in connecting to the mobile network.	
Basic		
Python	Mobile Service Provider Settings	
Management	Service Plan / APN:	
Network Status	Lise backup APN Retry the main APN after 0 minutes	
Connections		
Position	SIM PIN: (Optional)	
Applycor	Confirm SIM PIN:	
Top Talkers		
Administration	Username: (Optional)	
System Information	Password: (Optional)	
File Management	Confirm Password:	
X.509 Certificate Management		
Backup/Restore	Mabile Connection Sottings	
Update Firmware		
Factory Default Settings	Re-establish connection when no data is received for a period of time	

Una vez ingresada a la pestaña **mobile settings**, se deben ingresar los datos marcados con un circulo rojo. La opción **sim pin**, se ingresa solo si la sim tiene pin. En los cuadrados debajo de la imagen se muestran los datos solicitados para cada empresa de servicios de Internet.

Digit	ransPort WR21 (SN: 41	6884) Configuration and Managemen	t	
User : username	configuration - Network > Inte	erfaces > <u>Mobile</u>		
Home Wizards Configuration Network	 ✓ Interfaces > Ethernet ✓ Mobile Select a SIM to configure 	e from the list below		
Alarms System Remote Management Security	Settings on this page app	SIM: 1 (PPP 1) V IMSI: Unknown		
Position Applications Basic	Mobile Settings Select the service plan and connection settings used in connecting to the mobile network.			
Python Management Network Status Connections Position Event Log Analyser Top Talkers Administration System Information File Management X.509 Certificate Management Backup/Restore Update Firmware Factory Default Settings	Mobile Service Provider Service Plan / SIN Confirm SIN Userr Pass Confirm Pass Confirm Pass Confirm Pass	Settings / APN Use backup APN M PIN: (Optional) M PIN: sword (Optional) (Opti	Retry the main APN	after 0 minutes
[CLARO] APN: bam.clar User: clarochil Pass: clarochi	ochile.cl le le	[MOVISTAR] APN: web.tmovil.cl User: web pass: web	[EN] APN User Pass	TEL] : imovil.entelpcs.cl : entelpcs 5: entelpcs

Una vez finalizado lo anterior, se debe presionar apply.



Después de presionar apply, se debe presionar here.





User : username	Home
	Save current configuration to Config 0 (power up) 💌
Home	Save
Wizards	
Configuration	Save all configuration. This includes the following
Network	Save the current configuration to config 0
Alarms	Save the current firewall
System	 Save all sregisters on all ports to profile 0 Save all DAD parameters on all DADs to profile 0
Remote Management	Save all FAD parameters on all FADs to prome o
Security	Save All
Position	
Applications	
Basic	
Python	
Management	
Network Status	
Connections	
Position	
Event Log	
Analyser	
Top Talkers	
Administration	
System Information	
File Management	
×.509 Certificate Management	
Backup/Restore	
Update Firmware	
Factory Default Settings	
Execute a command	×



TransPort WR21 (SN: 416884) Configuration and Management







User : username

TransPort WR21 (SN: 416884) Configuration and Management

Home





User : username

Management - Connections

Network
Alarms
System
Remote Management
Security
Position
Applications
Basic
Python
Management
Network Status
Connections
Position
Event Log
Analyser
Top Talkers
Administration
System Information
File Management
X.509 Certificate Managem
Backup/Restore
Update Firmware
Factory Default Settings
Execute a command
Save configuration
Reboot

Logout

	▶ IP connections	
	PPP Connections	
	Virtual Private Networking (VPN)	
	Copyright © Digi International, Inc. All rights reserved.	
gement		
js		





User : username

^

<u>Management - Connections</u> > <u>PPP Connections</u>

Network
Alarms
System
Remote Management
Security
Position
Applications
Basic
Python
Management
Network Status
Connections
Position
Event Log
Analyser
Top Talkers
Administration
System Information
File Management
X.509 Certificate Management
Backup/Restore
Update Firmware
Factory Default Settings
Execute a command
Save configuration
Reboot

Logout

IP Connections			
▼ PPP Connections			
▶ PPP 0			
🕨 PPP 🧲 W-WAN (HSPA 3G)			
▶ PPP 2			
> PPP 3			
Virtual Private Networking (VPN)			

Copyright © Digi International, Inc. All rights reserved.





User : username













Ante cualquier inquietud, no dude con comunicarse con nosotros

soporte@wamtech.com



